

ELEMAX

ELEMAX SH7600EX-S PETROL GENERATOR OPEN



High-Quality Power Source: Equipped with a Sawafuji Generator and Honda GX390 Engine for Reliable Performance.

Specifications

Models				SH6500EX	SH7600EX
Type				R-type; 220V (50Hz) S-type; 220V (60Hz) D-type; 110/220V (60Hz) LD-type; 120/240V (60Hz)	
Generator	Frequency (Hz)			50, 60	
	Type			Self-Exciting, 2-pole, Field Rotating Type	
	Voltage Regulation System			AVR	
	Phase			Single	
	AC Output	Rated Power (KVA)	50Hz	5.0	5.6
			60Hz	5.6	6.5
		Maximum Power (kva)	50Hz	5.8	6.5
			60Hz	6.5	7.6
		Rated Voltage (V)		220 (R,S-type), 110/220 (D-type), 120/240 (LD-type)	
		DC Output (V-A)			12V-8.3A
Rated Power Factor (cosφ)			1.0		
Engine	Maker			HONDA	
	Models			GX340	GX390
	Displacement (CC)			389	389
	Net Power (kW)			3,600rpm	8
	Ignition System			Transistor	
	Oil Alert System			YES	
	Starting System			Recoil (OP; Electric)	
Others	L x W x H (mm)			708 x 548 x 493	
	Dry Weight (kg)			75	78
	Fuel Tank Capacity (liters)			28	
	Sound Level			50Hz	71
	[dB(A)/7m]			60Hz	75
	Continuous			50Hz	10
	Operating Hours (hr)			60Hz	7.9